

Multimeter

Nagman
Digital Multimeter

Portable, Handy, Easy to carry
& Sturdy case with grip

Basic Accuracy : $\pm 0.05\%$ F.S.

*Capability to Measure True RMS AC;
Perform Diode & Continuity Test*

Model

VC980+

- 4½ digit handheld Digital Multimeter
- Large LCD Screen
- Capability to Measure :
 - DC Voltage upto 1000 V
 - AC Voltage upto 750 V
 - DC & Ac Current upto 20 A
- Capacitance & Resistance upto 200 μ F & 200 M Ω
- Frequency : 200 KHz
- Capability to measure True RMS AC
- Capability to perform Diode & Continuity Test
- Low Battery Indication with Auto Power Off



(P.T.O)

SPECIFICATIONS

Basic Function	Range	Accuracy
DC Voltage	200 mV / 2V / 20 V / 200 V / 1000 V	$\pm(0.05\% + 3)$
AC Voltage	200 mV / 2V / 20 V / 200 V / 750 V	$\pm(0.8\% + 25)$
DC Current	200 μ A / 2 mA / 200 mA / 20 A	$\pm(0.5\% + 4)$
AC Current	200 mA / 20 A	$\pm(1.5\% + 25)$
Resistance	200 Ω / 2 k Ω / 20 k Ω / 200 k Ω / 2 M Ω / 200 M Ω	$\pm(0.2\% + 5)$
Capacitance	2 nF / 2 μ F / 200 μ F	$\pm(4.5\% + 50)$
Frequency	20 kHz / 200 kHz	$\pm(1.5\% + 25)$

STANDARD DELIVERY

- Digital Multimeter - Model VC980+
- 9V Alkaline Battery
- Operation Manual
- Test Leads
- Traceable Calibration Certificate

OPTIONAL

- Calibration Certificate from NABL Accredited – as per ISO/IEC 17025:2005 Laboratory

Product of

Nagman Instruments & Electronics (P) Ltd.

- Comprehensive Calibration Solutions (Standards / Systems / Packages / Software / Services)

Chennai – 600 123. INDIA.



Domestic Sales 044 – 2252 2800, 2252 3240 **Fax** 044 – 2252 3240 **E-Mail** mktgchennai@nagman.com
International Sales +91-44-26811704, 26811708 **Fax** +91-44-26811703 **E-Mail** exports@nagman.com

www.nagman.com

